


PLL 28.675.40.1/DALI

PL 28 (1xLED 97W 840/4000K 11830lm)

— C0/C180 cd / 1000 lm - - - C90/C270



	C0	C90	C180	C270
0°	283	283	283	283
30°	235	235	235	235
60°	121	121	121	121
90°	1	1	1	1
120°	33	32	33	32
150°	65	65	65	65
180°	76	76	76	76
cd / 1000 lm				

LDC unsuitable for cone representation.
The C0 angle is oversized.

η Efficiency	LED 122 lm/W
Direct/Indirect	↓ 79% / ↑ 21%
System Power	97 W
UGR Reflection factors	X=4H, Y=8H 70/50/20
UGR C0/C180	22.1
UGR C90/C270	22.2
CIE Flux Codes	48 79 96 79 100
Ra/CRI	> 80